



产品特性 Features



- ▶ 最大支持模拟通道16进16出和1路USB扩展录播通道，DSP处理总线结构，并且拥有人性化的操作软件界面，具有操作简单，集成控制功能强等特点。可以满足剧场、音乐厅、远程视频会议、体育场馆、教堂、会议中心、主题公园等公共扩声系统等多方面的应用需求。
- ▶ 控制通道名称支持中英文标识，快捷键开/关功能模块，通道支持DCA和GROUP编组功能等。
- ▶ 内置反馈抑制器、回声消除器（AEC）、自动混音器、路由器、哑音、相位、幻像供电、信号发生器（粉红噪声、白噪声、正弦波）、噪声门、压限器、31段均衡器、5段参量均衡器、自动增益、延时器、分频器、限幅器、信号指示表器等功能。
- ▶ 配置了RS-485接口，支持自动摄像跟踪功能；RS-232双向串行控制接口：可发送或接受控制，如视频矩阵、摄像机、中控等功能。
- ▶ 8通道自定义输入输出的GPIO（逻辑）可编程控制接口，可实现消防联动等功能。
- ▶ 支持多组场景预设，场景保存等多种功能，断电自动保护记忆功能。
- ▶ 带USB接口（支持录音及播放功能）。
- ▶ 带DANTE网络音频传输接口。
- ▶ 内置网页控制功能，在Windows、Android、iOS等平台上皆可快速操作，设备直联PC等设备登录预置IP网页就可以实现通道控制、场景调用、安装软件下载。
- ▶ 前面板具有每个输入通道和输出通道信号状态监测指示灯和信号过载监测指示灯、电源指示灯和工作状态指示灯。

- ▶ Support 16 input/output analog channels and 1 USB recorded broadcast channel, with DSP chip, has friendly and easy-to-use user interface, providing strong integrated control, can meet the various sound reinforcement needs of theaters, music halls, remote video conferences, stadiums, churches, meeting centers, theme parks.
- ▶ Support DCA and GROUP functions, have on/off shortcut keys.
- ▶ With powerful audio processors like: feedback suppressor, AEC, 31 segments GEQ, output channel 5 PEQ, noise gate, limiter, automatic gain, automatic mixer, router, frequency divider, threshold, filter, mute, phase, signal indicator and signal generator etc.
- ▶ With RS-485 interface, support intelligent automatic camera tracking function, RS-232 Bi-directional serial control interface: transmission or acceptance control, such as video matrix, camera, central control and other functions.
- ▶ 8 channels customized input/output programmable GPIO control interface, can achieve fire alarm function etc.
- ▶ Support scene preset function, automatic self-protective memory when power off.
- ▶ With USB connection (support record and play function).
- ▶ With DANTE network audio transmission interface.
- ▶ Independent software can work at Windows/Android/iOS.
- ▶ The front panel has signal status monitoring indicators, signal overload monitoring indicators, power indicator and operating status indicators for each input and output channel



DP-0808DANTE/DP-1212DANTE/DP-1616DANTE

矩阵数字音频处理器

Matrix Digital Audio Processor

DP SERIES

参数规格 Specifications

型号	DP-0808DANTE	DP-1212DANTE	DP-1616DANTE	A/D 动态范围	120dB
模拟输入通道	8	12	16	输入共模抑制	80dB@+24dBu@60Hz
模拟输出通道	8	12	16	输入阻抗	20KΩ balance , 10KΩ unbalance
网络通道输入	8	12	16	最大输入	24dBu
网络通道输出	8	12	16	D/A 动态范围	120dB
GPIO数量	8,可自由配置输入输出			通道隔离度	100dB
RJ45数量	1			频率响应	20Hz~20kHz(±0.5dB)
USB数量	1,可支持录播			总谐波失真(THD+N)	≤0.009%
RS232/RS485	1			输出阻抗	100Ω balance , 50Ω unbalance
DANTE网络	主网口+备份网口			最大输出	17dBu
DANTE网络延时	<1ms			工作电源	AC 110V/220V 50Hz/60Hz
最大模拟增益	-51dB			工作温度	0~40°C
幻象供电	48V			输入输出量化	48kHz/24bit

ITEM NO.	DP-0808DANTE	DP-1212DANTE	DP-1616DANTE	A/D dynamic range	120dB
Analog input	8	12	16	Quantization bits	48kHz/24bit
Analog output	8	12	16	Dynamic/Analogy range	120dB
Network channel input	8	12	16	Input CMMR	80dB@+24dBu@60Hz
Network channel output	8	12	16	Input impedance	20kΩ balance , 10kΩ unbalance
GPIO	8			Output impedance	100Ω balance , 50Ω unbalance
RJ45	1			D/A dynamic range	120dB
USB port	1, support recording and broadcasting			Channel isolation , 1kHz	100dB
RS232/RS485	1			Frequency response	20~20kHz(±0.5dB)
DANTE network	main port+Aux port			THD+N	≤0.009%
DANTE network delay	<1ms			Temperature	0~40°C
Maximum analog gain	-51dB			Max level	17dBu
Phantom power	48V			Power supply	AC 110V/220V 50Hz/60Hz



广州市锐丰智能科技有限公司 A:广东省广州市番禺区市莲路石楼路段10号
T:020-3928 0043 F:020-39280123-8014 E:info@rfintell.com Z:511447 www.rfintell.com

Guangzhou Ruifeng Intelligence Technology Co., Ltd Address: No.10,Shilou Section,Shilian Road,Panyu District,Guangzhou,Guangdong,China
T:+86 2039280083 Mobile: +86 13609092324 F:+86-20-39280123-8014 E: mail:sales@rfintell.com Z:511447 www.rfintell.com

